

Reliability Analysis Update



Transmission Expansion Advisory Committee August 10, 2017

PJM TEAC – 8/10/2017 PJM©2017



2017 RTEP Evaluation of 2022 Conditions

PJM TEAC – 8/10/2017 2 PJM©2017



2017 RTEP Progress Update

May 18, 2017

- Preliminary 2022 Summer results posted
- Baseline N-1 Thermal
- Generator Deliverability Thermal

July 5, 2017

- Posted additional preliminary 2022 Summer results:
 - N-1-1 Thermal & Voltage, Load Deliverability, N-1 Voltage
- Preliminary 2022 Light Load results and 2022 Winter results
- Noted determination of flowgates anticipated be excluded from window.

July 11, 2017

2017 Proposal Window #1 Opened


Friday, August 25, 2017 (anticipated)

2017 Proposal Window #1 Close



Analysis of 2022 - Violations


- 190 flowgates
- 2022 conditions
- Summer, Winter & Light Load
- Includes both voltage and thermal violations





2022 Analysis Violations

Count of FG #	Gen Deliv	Load Deliv	N-1 Load Drop	N-1 Thermal	N-1 Voltage High	N-1-1 Thermal	Voltage High	Grand Total
69	3	1	-		_			4
MAAC	3	1						4
South								0
115	8						2	10
MAAC	7						2	9
South	1							1
138	51	2	2	14		8		77
MAAC	1	2				2		5
West	50		2	14		6		72
161	14			3		2		19
West	14			3		2		19
230	33					1		34
MAAC	27					1		28
South	6							6
345	6				5		35	46
MAAC					5		35	40
West	6							6
Grand	445	2	2	47	_	44	27	100
Total	115	3	2	17	5	11	37	190





2017 Proposal Window Update

PJM TEAC – 8/10/2017 6 PJM©2017



2017 RTEP Proposal Window 1 - Overview


Overview of 2022 Results Total of 190 flowgates identified

- 41 to be included in the window
 - 33 in West region
 - 5 in the South region
 - 3 in the MAAC region
- 149 flowgates excluded
 - Immediate need (PJM OA 1.5.8(m)) (Includes Retired Generator related)
 - < 200kV (PJM OA 1.5.8(n))



2017 RTEP Proposal Window 1 - Violations

- 41 flowgates are window eligible
- Includes both voltage and thermal violations






2017 RTEP Proposal Window 1 - Overview

Window Eligible Yes

Count of FG #	Gen Deliv 21	N-1 Thermal 6	Grand Total 27
West	21	6	27
230	8		8
MAAC	3		3
South	5		5
345	6		6
West	6		6
Grand Total	35	6	41





2017 RTEP Proposal Window 1 – MAAC Results

 3 flowgates are window eligible






2017 RTEP Proposal Window 1 – MAAC Results

Region MAAC Window Eligible Yes


Count of FG #	Gen Deliv	Grand Total
230	3	3
DPL	2	2
Summer	2	2
PEPCO	1	1
Winter	1	1
Grand Total	3	3





2017 RTEP Proposal Window 1 – South Results

- 5 flowgates are window eligible
- Voltage
- Thermal






2017 RTEP Proposal Window 1 – South Results

Region South Window Eligible Yes


Count of FG #	Gen Deliv	Grand Total
230	5	5
DVP	5	5
Summer	5	5
Grand Total	5	5





2017 RTEP Proposal Window 1 – West Results

- 33 flowgates are window eligible
- Voltage
- Thermal






2017 RTEP Proposal Window 1 – West Results


Region West Window Eligible Yes

Count of FG #	Gen Deliv	N-1 Thermal	Grand Total
138	21	6	27
AP	16	1	17
Summer	16	1	17
DEOK	5	5	10
Summer	5	5	10
345	6		6
AEP	4		4
Winter	4		4
DEOK	2		2
Winter	2		2
Grand Total	27	6	33





2017 RTEP Proposal Window 1 – All Results





Dominion Update End of Life Criteria



Baseline Reliability - TO Criteria Violation Line #211 and #228 Chesterfield to Hopewell Partial Rebuild

Date Project Last Presented: 7/13/2017 TEAC

Problem Statement: Dominion "End of Life Criteria"

- 230kV Lines #211 and #228 run 11 miles from Chesterfield to Hopewell and are double circuit lines
- Approximately 8 miles of the lines were built on double circuit weathering steel (Corten) towers in 1969. Field reports and condition assessment indicate the Corten structures are in poor condition. Static fiber is also at end of life.
- These lines provide critical outlet for Chesterfield Power station along with HCF and Polyester.

Recommended Solution:


- Rebuild 8 miles of Line #211 and #228 to current standard. Proposed conductor is 2-636 ACSR. Summer emergency rating of the rebuilt section is 1046 MVA. Summer emergency rating of the entire lines after rebuild is 477 MVA with the remaining 3 mile section being the most limiting conductor. (b2922)
- Structures being considered include double circuit steel pole and double circuit galvanized steel tower.
- Fiber on the entire line will be replaced.

Alternatives: Replace fiber. Rebuild entire 11 miles of lines to current standard. Summer emergency rating of the new lines is 1046 MVA. Estimated project cost is \$34.1M.

Estimated Project Cost: \$28.1 M

Projected IS Date: Dec 2020 Project Status: Conceptual

Dominion Transmission Zone





Dominion Transmission Zone

Baseline Reliability - TO Criteria Violation Line #2144 Winfall to Swamp is at its End of Life

Problem Statement: Dominion "End of Life Criteria"

- 230kV Line #2144 Winfall Swamp was constructed mostly on wood H frames in 1968. This line needs to be rebuilt to current standards based on Dominion's "End of Life" criteria. The existing summer emergency rating of this line is 478 MVA. The existing conductor is 1109 ACAR (24/13).
- Rebuild is needed because:
 - Permanent retirement of Line #2144 changes 230kV Line #247 Suffolk Swamp from a 230kV network line to a 31 mile long radial line serving 3900 customers.
 - The MW-mile for Line #247 Suffolk Swamp would be 685 MW-mile based on the Winter 2025/26 projection.
 Dominion's 700 MW-mile radial line criteria would be violated if 0.5 MW or more of new load were added in the future.
 - Contingencies result in reliability violations (low voltage) under stress case conditions (solar generation off line)

Potential Solution:

• Rebuild 230kV Line #2144 from Winfall to Swamp (4.3 miles) to current standards with a standard conductor (bundled 636 ACSR) having a summer emergency rating of 1047 MVA at 230kV.

Alternatives: There are no other feasible alternatives that will maintain this network line.

Estimated Project Cost: \$6 M Possible IS Date: 12/30/2022 Project Status: Conceptual

COLOR	VOLTAGE	TRANSMISSION LINE NUMBER
_	500 KV.	500 thru 599
_	230 KV.	200 thru 299 & 2000 thru 2099
_	115 KV.	1 thru 199
_	138 KV.	AS NOTED
	69 KV.	AS NOTED

OAK RIDGE YADKIN 74 GRAS GF BRI
D Sattolk SUFFOLK 2110
16
247
ates
Pasquot TANGLEWOOD DF
2144 2020 P.
S.HERTFORD Perquimans



Baseline Reliability - TO Criteria Violation

Line #567 River Crossing Rebuild


Date Project Last Presented: 4/25/2017 SRRTEP

Problem Statement: Dominion "End of Life Criteria"

- This project was previously presented as a Supplemental Project (s1280)
- Baseline project classification due to characteristics of the problem
- Dominion filed an application with the Virginia SCC in December of 2016 to replace four structures of 500kV Line #567 (Chickahominy – Surry PS).
- Two of these structures are located in the James River and are approximately 400 feet tall and the other two structures are located on the rivers edge.
- These structures have deteriorated to a point that they need to be replaced. A specialized conductor was used in the construction of the river crossing which limits the line to 1954 MVA.
- This is the only location on Dominion's system that this conductor is used.
 - Loss of Line #567 results in multiple Generation Deliverability violations:
 - 230kV Line #259 Chesterfield Basin is overloaded for the loss of Line #563 Carson Midlothian or the loss of 230kV Line #217 Chesterfield – Lakeside
 - 230 kV Line #2154 Skiffes Creek Kings Mill is overloaded for the loss of Line # 563 Carson – Midlothian
 - 230kV Line #2154 Skiffes Creek Kings Mill Penniman Waller is overloaded for stuck breaker 56372 at Carson
 - 500kV 230 kV Transformer at Carson is overloaded for stuck breaker 562T563 at Carson
 - 230kV Line #259 Chesterfield Basin is overloaded for stuck breaker 205T217 at Chesterfield

Continued on next slide...

Dominion Transmission Zone Baseline Project





Dominion Transmission Zone Baseline Project

Continued from previous slide...

Potential Solution:

 Rebuild the four structures using galvanized steel and replace the river crossing conductor with 3-1534 ACSR.


• This will increase the 500kV Line #567 line rating from 1954 MVA to 2600 MVA.

Alternatives: No feasible alternatives

Estimated Project Cost: \$41 M

Possible IS Date: 12/30/2017

Project Status: Engineering





Short Circuit Projects

PJM TEAC – 8/10/2017 22 PJM©2017



 The China Tap 230kV breaker 'CS15' is overstressed


Recommended Solution:

 Replace China Tap 230kV breaker 'CS15' with a 63kA breaker (b2923)

Estimated Project Cost:

\$603 K

Required IS Date: 6/1/2019





 The Emilie 230kV breakers 'CS15' and 'CS25' are overstressed


Recommended Solution:

 Replace Emilie 230kV breakers 'CS15' and 'CS25' with 63kA breakers (b2924 & b2925)

Estimated Project Cost:

\$603 K

Required IS Date: 6/1/2019





 The Chichester 230kV breaker '215' is overstressed


Recommended Solution:

 Replace Chichester 230kV breaker '215' with a 63kA breaker (b2926)

Estimated Project Cost:

\$342 K

Required IS Date: 6/1/2019





 The Plymouth Meeting 230kV breaker '125' is overstressed


Recommended Solution:

 Replace Plymouth Meeting 230kV breaker '125' with a 63kA breakers (b2927)

Estimated Project Cost:

\$342 K

Required IS Date: 6/1/2019





2017 RTEP Next Steps

PJM TEAC – 8/10/2017 27 PJM©2017



- Anticipate closing the 2017 Window #1 on Friday, 8/15/2017
- Present preliminary recommendations for immediate need violations and other violations that were excluded from the window

- Anticipate 15 year reliability results
- 18 month RTEP cycle Update



Upcoming TEAC Meetings and anticipated PJM Board Review

9/14 - TEAC Reliability Analysis Update

10/12 - TEAC Reliability Analysis Update

10/17 - PJM Board of Managers Review

11/9 – TEAC Reliability Analysis Update

12/4 – PJM Board of Managers Review

(If necessary, additional online/teleconference meetings to be held to review potential and recommended solutions)



Questions?

Email: RTEP@pjm.com

PJM TEAC – 8/10/2017 30 PJM©2017



- 8/7/2017 Original Version Posted to PJM.com
- 8/9/2017 Updated Version Posted to PJM.com
 - Slides 4,5,7 updated with current data for # of flowgates posted in window
 - Slide #19 updated to include information regarding violations under stress case conditions.

PJM TEAC – 8/10/2017 9JM©2017